



## Adding Project Variables to a Modular Device Compass Navigator

- 1. In Navigator, edit module for desired device (.mod mode, not .ksp mode)
- 2. Select device from System Designer tree
- 3. In the properties window Bi-Directional Driver section, press the blue block button to open the script editor (fig.3)
- 4. In the Script Editor, key applicable text from below (fig. 4/5)
  - a. Integer variable: extern int iVariableName;
  - b. String variable: extern string sVariableName;
  - c. Boolean variable: extern bool bVariableName;
  - d. **Double variable**: extern double dVariableName;

Link: Variable types and definitions


- Press COMPILE and receive confirmation (fig. 4/5). Press OK
- 6. The created variables should now show up in the Project Variables folder of the project that the module is being used in

## **Example Figures**

3.

Bi-Directional Driver

4/5.





Key Digital® Systems :: 521 East 3rd Street :: Mount Vernon, NY 10553 Phone : 914.667.9700 Fax : 914.668.8666 Web : www.keydigital.com